

**SR408**  
**Konvansiyonel Yangın Sireni**

**ÖZELLİKLER**

Çalışma Voltaj Aralığı	:16 to 30 VDC
Maksimum Alarm Akımı	: 30mA
Çalışma Nem Oranı	:10% to 93% (Bağıl nem, Yoğuşmasız)
Çalışma Sıcaklığı	:-10°C to 50°C
Ebatları	: 10x6.5 cm
Ses Şiddeti	: 100 dB
Koruma Sınıfı	: IP40

**GENEL AÇIKLAMALAR**

SR408 konvansiyonel yangın sireni, konvansiyonel ve adresli yangın sisteminde, yangın veya acil durumların, sesli uyarı bildirilmesi için kullanılır. Adresli sistemlerde ekstra bir kablo üzerinden bağlantısı yapılır. DD-T tabanına uyumludur.

**KURULUM**



Konvansiyonel Yangın Sireni iki parçadan oluşur: bir taban ve içerisinde elektronik kartın bulunduğu bir üst parça. Önce taban parçası duvara sabitlenir. Zone kabloları üst parçada bulunan taban metallere bağlanır. Zone için 1 adet artı (+) 1 adet eksi (-) terminal vardır. Metalin 1 numaralı ayağı (+) 2 numaralı ayağı (-) dir. Ardeşık bağlantılarda paralel bağlantı yapılır. Bağlantılar yapılırken yönlere dikkat edilmelidir. Son siren bağlantısı yapıldıktan sonra sonlandırma direnci atılır.

**KABLOLAMA**

Kablolama için uygun kesitte kablo seçimi yapılmalıdır. Kablolamada hata yapılmaması için içerisinde farklı renklerde tel olan kablo kullanılmalıdır. Kablolamada hata yapılması durumunda yangın anında yanlış bilgilendirme meydana gelebilir. Yangın butonu montajı ve bağlantısı sırasında enerjinin kesilmesi gerekir.

**TWO-YEAR LIMITED WARRANTY**

We warrant its enclosed smoke detector to be free from defects in materials and workmanship under normal use and service for a period of three years from date of manufacture. We make no other express warranty for this smoke detector. No agent, representative, dealer, or employee of the Company has the authority to increase or alter the obligations or limitations of this Warranty. The Company's obligation of this Warranty shall be limited to the repair or replacement of any part of the smoke detector which is found to be defective in materials or workmanship under normal use and service during the two year period commencing with the date of manufacture. After calling Code Security's technical support number for a Return Authorization number, send defective units postage prepaid to Code Security local representative office. Please include a note describing the malfunction and suspected cause of failure. The Company shall not be obligated to repair or replace units which are found to be defective because of damage, unreasonable use, modifications, or alterations occurring after the date of manufacture. In no case shall the Company be liable for any consequential or incidental damages for breach of this or any other Warranty, expressed or implied whatsoever, even if the loss or damage is caused by the Company's negligence or fault. Some states do not allow the exclusion or limitation of incidental or consequential damages, so the above limitation or exclusion may not apply to you. This Warranty gives you specific legal rights, and you may also have other rights which vary from state to state.